





SINGLE CHOKES Symetrical (Differential Mode) Interference Suppressor Storage, PFC Chokes



ELEKTRONİK ELEKTRİK PLASTİK MAKİNE
VE TEÇHİZAT SAN. VE TİC. LTD. ŞTİ.

12 300 0010
Istanbul, 2013-01-02

Choke No:	Inductor Core Alloy	Effective Frequency Interval	Specified for a usage of Storage Choke	Inductance	Current	Core Type	Configuration Straight: Plain Dxx: Vertical/Plated Bxx: Vertical/Horizontal Covered
SC-1	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.8uH	5 A	R3311F	Straight
SC-2	Ni-Zn	[10MHz,1000MHz]		1.9uH	1.6 A	R1003U-bl	Straight
SC-3	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	2.3uH	27 A	R1710F	Straight
SC-4	Ni-Zn	[10MHz,1000MHz]		4uH	6 A	R1003U-bl	Straight
SC-5	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	4.1uH	1 A	R1003F	Straight
SC-6	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	4.1uH	30 A	R2408F	Straight
SC-7	Ironpowder-D	[50-300KHz]	•	5uH	8.4 A	R1705CD	Straight
SC-8	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	8.2uH	1 A	R1003F	Straight
SC-9	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	10uH	3 A	R1003F	B6
SC-10	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	10uH	10 A	R1305F	B1
SC-11	Mollypermalloy	reversing current	PFC/Storage Choke	10uH	20 A	R2711MPP	Straight
SC-12	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	11uH	1.5 A	R1003F	Straight
SC-13	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	12.6uH	1 A	R1003F	Straight
SC-14	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	15uH	3 A	R1003F	Straight
SC-15	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	15uH	3 A	R1003F	B6
SC-16	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	20uH	3.8 A	R1305F	Straight
SC-17	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	21uH	2 A	R1003F	Straight
SC-18	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	21uH	10.2 A	R2006F	Straight
SC-19	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	22uH	3 A	R1003F	Straight
SC-20	Ironpowder-D	[50-300KHz]	•	22uH	5 A	R2006D	Straight
SC-21	Ironpowder-D	[50-300KHz]	•	22uH	5 A	R2006D	D30
SC-22	Ironpowder-D	[50-300KHz]	•	26uH	11.4 A	R2006D	Straight
SC-23	Ironpowder-D	[50-300KHz]	•	26uH	14 A	R2408D	Straight
SC-24	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	30uH	10 A	R2711F	Straight
SC-25	Mollypermalloy	reversing current	PFC/Storage Choke	30uH	66 A	R4718MPP	Straight
SC-26	Mollypermalloy	reversing current	PFC/Storage Choke	30uH	85 A	R4736MPP	Straight
SC-27	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	32uH	2 A	R1003F	Straight

(listed according to the increasing inductive value, please contact us for different values those do not exist in the list.)



AKE Elektronik Elektrik Plastik Makine ve Teçhizat San. Ve Tic. Ltd. Şti.

5900 Sokak No: 14 / A Karabağlar -İZMİR

Tel: 0090 232 254 39 29 - 0090 232 254 3828 Fax: 0090 232 254 16 60

Web: <http://www.akeelektronik.com> e-mail: ake@akeelektronik.com



SC-28	Ironpowder-D	[50-300KHz]	•	33uH	0.8 A	R1003D	Straight
SC-29	Ironpowder-D	[50-300KHz]	•	33uH	1.3 A	R1305D	Straight
SC-30	Ironpowder-D	[50-300KHz]	•	33uH	1.5 A	R1003D	Straight
SC-31	Ironpowder-D	[50-300KHz]	•	33uH	2.8 A	R1305D	Straight
SC-32	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	36uH	38.5 A	R3311F	Straight
SC-33	Ironpowder-D	[50-300KHz]	•	37uH	2.2 A	R1305D	Straight
SC-34	Ironpowder-D	[50-300KHz]	•	38uH	3 A	R2006D	D30
SC-35	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	40uH	10 A	R2711F	Straight
SC-36	Mollypermalloy	reversing current	PFC/Storage Choke	40uH	10 A	R2711MPP	Straight
SC-37	Mollypermalloy	reversing current	PFC/Storage Choke	47uH	8.2 A	R2711MPP	Straight
SC-38	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	50uH	5 A	R1705F	Straight
SC-39	Mollypermalloy	reversing current	PFC/Storage Choke	50uH	70 A	R4736MPP	Straight
SC-40	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	55uH	-	R1305F	Straight
SC-41	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	55uH	15 A	R3311F	Straight
SC-42	Mollypermalloy	reversing current	PFC/Storage Choke	55uH	80 A	R4736MPP	Straight
SC-43	Mollypermalloy	reversing current	PFC/Storage Choke	60uH	41 A	R4718MPP	Straight
SC-44	Mollypermalloy	reversing current	PFC/Storage Choke	72uH	41 A	R4718MPP	Straight
SC-45	Ironpowder-D	[50-300KHz]	•	74uH	3 A	R2006D	Straight
SC-46	Ironpowder-D	[50-300KHz]	•	77uH	3 A	R2006D	D30
SC-47	Ironpowder-D	[50-300KHz]	•	77uH	3 A	R1705D	D10
SC-48	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	80uH	4 A	R1706F	Straight
SC-49	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	80uH	4 A	R1706F	Straight
SC-50	Mollypermalloy	reversing current	PFC/Storage Choke	82uH	55 A	R4736MPP	Straight
SC-51	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	100uH	1 A	R1003F	Straight
SC-52	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	100uH	1 A	R1003F	Straight
SC-53	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	100uH	2 A	R1305F	Straight
SC-54	Ironpowder-D	[50-300KHz]	•	100uH	3 A	R2006D	Straight
SC-55	Ironpowder-D	[50-300KHz]	•	100uH	3 A	R1705D	Straight
SC-56	Ironpowder-D	[50-300KHz]	•	100uH	3 A	R1705D	Straight
SC-57	Ironpowder-D	[50-300KHz]	•	100uH	3 A	R2006D	Straight
SC-58	Ironpowder-D	[50-300KHz]	•	100uH	3 A	R2006D	Straight
SC-59	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	100uH	5 A	R1705F	Straight
SC-60	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	100uH	5 A	R2006F	Straight
SC-61	Ironpowder-D	[50-300KHz]	•	100uH	5 A	R2408D	Straight
SC-62	Ironpowder-D	[50-300KHz]	•	100uH	7 A	R2408D	Straight
SC-63	Ironpowder-D	[50-300KHz]	•	100uH	7.3 A	R2408D	Straight
SC-64	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	100uH	10 A	R3311F	Straight
SC-65	Mollypermalloy	reversing current	PFC/Storage Choke	101uH	36 A	R4718MPP	Straight
SC-66	Ironpowder-D	[50-300KHz]	•	104uH	3 A	R1705D	Straight
SC-67	Ironpowder-D	[50-300KHz]	•	110uH	3 A	R2408D	D30

(listed according to the increasing inductive value, please contact us for different values those do not exist in the list.)



AKE Elektronik Elektrik Plastik Makine ve Teçhizat San. Ve Tic. Ltd. Şti.
5900 Sokak No: 14 / A Karabağlar -İZMİR
Tel: 0090 232 254 39 29 - 0090 232 254 3828 Fax: 0090 232 254 16 60
Web: <http://www.akeelektronik.com> e-mail: ake@akeelektronik.com



SC-68	Mollypermalloy	reversing current	PFC/Storage Choke	136uH	15 A	R4718MPP	Straight
SC-69	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	150uH	0.8 A	R1003F	Straight
SC-70	Ironpowder-D	[50-300KHz]	•	150uH	3 A	R2006D	Straight
SC-71	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	150uH	3 A	R1705F	Straight
SC-72	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	150uH	3 A	R1705F	Straight
SC-73	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	150uH	3 A	R1705F	Straight
SC-74	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	150uH	3 A	R1705F	D10
SC-75	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	150uH	15 A	R3311F	D50
SC-76	Mollypermalloy	reversing current	PFC/Storage Choke	150uH	18.6 A	R2722MPP	Straight
SC-77	Mollypermalloy	reversing current	PFC/Storage Choke	150uH	25 A	R4718MPP	Straight
SC-78	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	162uH	5 A	R2711F	Straight
SC-79	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	170uH	10 A	R2711F	Straight
SC-80	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	180uH	1.8 A	R1305F	Straight
SC-81	Mollypermalloy	reversing current	PFC/Storage Choke	180uH	25 A	R4718MPP	Straight
SC-82	Ironpowder-D	[50-300KHz]	•	183uH	5 A	R2408D	Straight
SC-83	Ironpowder-D	[50-300KHz]	•	200uH	3 A	R2408D	Straight
SC-84	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	220uH	0.2 A	R1003F	B6
SC-85	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	220uH	0.2 A	R1003F	Straight
SC-86	Ironpowder-D	[50-300KHz]	•	220uH	0.5 A	R1003D	Straight
SC-87	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	220uH	0.9 A	R1003F	Straight
SC-88	Ironpowder-D	[50-300KHz]	•	220uH	1 A	R1305D	Straight
SC-89	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	220uH	1.5 A	R1305F	Straight
SC-90	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	220uH	1.8 A	R1305F	Straight
SC-91	Ironpowder-D	[50-300KHz]	•	220uH	2 A	R1705D	Straight
SC-92	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	240uH	1.6 A	R1705F	Straight
SC-93	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	240uH	3.5 A	R1705F	Straight
SC-94	Ironpowder-D	[50-300KHz]	•	260uH	1 A	R1305D	Straight
SC-95	Ironpowder-D	[50-300KHz]	•	260uH	1 A	R1305D	Straight
SC-96	Ironpowder-D	[50-300KHz]	•	260uH	1 A	R1305D	D10
SC-97	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	280uH	1.5 A	R1305F	B1
SC-98	Ironpowder-D	[50-300KHz]	•	280uH	2.5 A	R2006D	B3
SC-99	Ironpowder-D	[50-300KHz]	•	280uH	2.5 A	R2006D	B3
SC-100	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	280uH	3 A	R1706F	D30
SC-101	Ironpowder-D	[50-300KHz]	•	300uH	1.7 A	R2006D	Straight
SC-102	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	300uH	1.7 A	R1705F	Straight
SC-103	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	300uH	2 A	R1705F	Straight
SC-104	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	300uH	4 A	R2006F	Straight
SC-105	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	330uH	0.6 A	R1003F	Straight
SC-106	Ironpowder-D	[50-300KHz]	•	330uH	1 A	R1305D	Straight
SC-107	Ironpowder-D	[50-300KHz]	•	330uH	1 A	R1305D	B1

(listed according to the increasing inductive value, please contact us for different values those do not exist in the list.)



AKE Elektronik Elektrik Plastik Makine ve Teçhizat San. Ve Tic. Ltd. Şti.
 5900 Sokak No: 14 / A Karabağlar -İZMİR
 Tel: 0090 232 254 39 29 - 0090 232 254 3828 Fax: 0090 232 254 16 60
 Web: <http://www.akeelektronik.com> e-mail: ake@akeelektronik.com



SC-108	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	330uH	1.5 A	R1305F	Straight
SC-109	Ironpowder-D	[50-300KHz]	•	330uH	1.5 A	R1705D	Straight
SC-110	Ironpowder-D	[50-300KHz]	•	330uH	3 A	R2408D	Straight
SC-111	Ironpowder-D	[50-300KHz]	•	330uH	3 A	R2408D	D30
SC-112	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	330uH	4 A	R2006F	Straight
SC-113	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	330uH	5.2 A	R2408F	Straight
SC-114	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	380uH	2 A	R1706F	Straight
SC-115	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	400uH	5 A	R2711F	Straight
SC-116	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	400uH	7 A	R3311F	Straight
SC-117	Mn-Zn	[500KHz-10MHz]		400uH	9.2 A	R1405X	Straight
SC-118	Mollypermalloy	reversing current	PFC/Storage Choke	403uH	3 A	R2711MPP	Straight
SC-119	Nickel-Ironpowder	reversing current	PFC/Storage Choke	405uH	2.5 A	R58120HF	Straight
SC-120	Nickel-Ironpowder	reversing current	PFC/Storage Choke	405uH	2.5 A	R58120HF	Straight
SC-121	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	440uH	0.6 A	R1305F	Straight
SC-122	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	470uH	0.2 A	R1003F	Straight
SC-123	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	470uH	0.8 A	R1305F	Straight
SC-124	Nickel-Ironpowder	reversing current	PFC/Storage Choke	484uH	2.3 A	R58120HF	Straight
SC-125	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	500uH	1 A	R1305F	Straight
SC-126	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	500uH	2 A	R1705F	Straight
SC-127	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	500uH	2.5 A	R1705F	Straight
SC-128	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	500uH	2.5 A	R1705F	D30
SC-129	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	500uH	5 A	R3311F	Straight
SC-130	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	500uH	6 A	R3311F	Straight
SC-131	Ironpowder-D	[50-300KHz]	•	515uH	3 A	R2408D	Straight
SC-132	Mn-Zn	[500KHz-10MHz]		540uH	3 A	R1003X	Straight
SC-133	Nickel-Ironpowder	reversing current	PFC/Storage Choke	583uH	2.1 A	R58120HF	Straight
SC-134	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	680uH	1 A	R1706F	Straight
SC-135	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	680uH	1 A	R1705F	Straight
SC-136	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	745uH	7 A	R3311F	Straight
SC-137	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	804uH	3.8 A	R2711F	Straight
SC-138	Mollypermalloy	reversing current	PFC/Storage Choke	820uH	3 A	R2711MPP	Straight
SC-139	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	905uH	1.5 A	R1710F	Straight
SC-140	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1mH	0.25 A	R1003F	Straight
SC-141	Ironpowder-D	[50-300KHz]	•	1mH	0.25 A	R1003D	Straight
SC-142	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1mH	0.8 A	R1305F	Straight
SC-143	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1mH	1 A	R1705F	Straight
SC-144	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1mH	1.5 A	R2006F	Straight
SC-145	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1mH	1.85 A	R2006F	Straight
SC-146	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1mH	2.3 A	R2408F	Straight
SC-147	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1mH	6 A	R3311F	Straight

(listed according to the increasing inductive value, please contact us for different values those do not exist in the list.)



AKE Elektronik Elektrik Plastik Makine ve Teçhizat San. Ve Tic. Ltd. Şti.
 5900 Sokak No: 14 / A Karabağlar - İZMİR
 Tel: 0090 232 254 39 29 - 0090 232 254 3828 Fax: 0090 232 254 16 60
 Web: <http://www.akeelektronik.com> e-mail: ake@akeelektronik.com



SC-148	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.14mH	5 A	R3311F	Straight
SC-149	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.2mH	0.6 A	R1305F	B1
SC-150	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.2mH	2 A	R2006F	Straight
SC-151	Mn-Zn	[500KHz-10MHz]		1.2mH	2 A	R1003X	Straight
SC-152	Mn-Zn	[500KHz-10MHz]		1.2mH	2 A	R1405X	Straight
SC-153	Mn-Zn	[500KHz-10MHz]		1.2mH	2 A	R1003X	D10
SC-154	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.28mH	5 A	R3311F	Straight
SC-155	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.32mH	3 A	R3311F	Straight
SC-156	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.36mH	5 A	R3322F	Straight
SC-157	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.3mH	4 A	R3311F	Straight
SC-158	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.5mH	3 A	R3311F	Straight
SC-159	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	1.5mH	3 A	R3311F	D50
SC-160	Ironpowder-D	[50-300KHz]	•	2.2mH	0.5 A	R1305D	Straight
SC-161	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	2.5mH	0.5 A	R1305F	Straight
SC-162	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	2.5mH	0.5 A	R2006F	Straight
SC-163	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	3.3mH	0.4 A	R1305F	Straight
SC-164	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	3.3mH	0.5 A	R1305F	Straight
SC-165	Ironpowder-F	[50-400Hz] ~1MHz	up to 50KHz	3.6mH	0.4 A	R1705F	Straight
SC-166	Nickel-Ironpowder	reversing current	PFC/Storage Choke	4.2mH	0.4 A	R58120HF	Straight
SC-167	Mn-Zn	[500KHz-10MHz]		32mH	0.5 A	R1405X	B1

(listed according to the increasing inductive value, please contact us for different values those do not exist in the list.)



AKE Elektronik Elektrik Plastik Makine ve Teçhizat San. Ve Tic. Ltd. Şti.
 5900 Sokak No: 14 / A Karabağlar - İZMİR
 Tel: 0090 232 254 39 29 - 0090 232 254 3828 Fax: 0090 232 254 16 60
 Web: <http://www.akeelektronik.com> e-mail: ake@akeelektronik.com

